



Combi-12-Flexi small

- ▣ 2 x Flexi-6
 - ▣ 1 x Ventus-12
- Amplifier recommendation:
- ▣ Powersoft T304, 4 x 750 W/8 Ω, 4 x 750 W/4 Ω
 - ▣ Powersoft T604, 4 x 1.250 W/8 Ω, 4 x 1.500 W/4 Ω

Combi-12sp-Flexi small

- ▣ 1 x Flexi-6
- ▣ 1 x Ventus-12sp

Flexi-6

Frequency range	68 Hz - 21 kHz (- 10 dB) 100 Hz - 20,5 kHz (+/- 3 dB)
Coverage range	asymmetric 100° to 50° x 55°
Power handling	125 W AES / 2500 W program / 500 W peak at 16 Ω
Sound pressure	112 dB SPL AES / 115 dB SPL program / 118 dB SPL peak
Components	LF: 1 x 6,5" bass-midrange driver HF: 1 x 1" Compression driver
Connectors	2 x Neutrik NL4 Speakon IN/OUT (loop through), configuration: 1+/1-
Dimensions	372 (h) x 190 (w) x 217 mm (d)

Ventus-12/12sp

Lower cut-off frequency	37 Hz (- 10 dB) 46 Hz (+/- 3 dB)
Power handling	1.000 W AES / 2.000 W program / 4.000 W peak at 8 Ω
Sound pressure	126 dB SPL AES / 129 dB SPL program / 132 dB SPL peak
Components	1 x 12" woofer with 4" voice coil
Connectors	2 x Neutrik NL4 Speakon IN/OUT (loop through), configuration: 2+/2-
Dimensions	368 (h) x 480 (w) x 500 mm (d)
Amplifier	4.6 kW, three channels
Power output CH1	2.600 W/ 8 Ω, 2.200 W/ 4 Ω
Power output CH2 & CH3	750 W/ 8 Ω, 1.000 W/ 4 Ω, 750 W/ 2 Ω

