



Combi-18-Powerstick large

2 x Powerstick-6

4 x Ventus-18

Amplifier recommendation:

2 x Powersoft X4, 4 x 1.600 W/8 Ω, 4 x 3.000 W/4 Ω

2 x Powersoft T604, 4 x 1.250 W/8 Ω, 4 x 1.500 W/4 Ω

Combi-18sp-Powerstick large

2 x Powerstick-6

2 x Ventus-18

2 x Ventus-18sp

Powerstick-6

Frequency range	70 Hz - 22 kHz (- 10 dB) 140 Hz - 20 kHz (+/- 3 dB)
Coverage range	asymmetric 100° to 50° x 55°
Power handling	500 W AES / 1.000 W program / 2.000 W peak at 4 Ω
Sound pressure	123 dB SPL AES / 126 dB SPL program / 129 dB SPL peak
Components	LF: 4 x 6,5" Bass-midrange driver HF: 1 x 1" Compression driver
Connectors	2 x Neutrik NL4 Speakon IN/OUT (loop through), configuration: 1+/1-
Dimensions	985 (h) x 220 (w) x 338 mm (d)

Ventus-18/18sp

Lower cut-off frequency	28 Hz (- 10 dB) 34 Hz (- 3 dB)
Power handling	1.200 W AES / 2.400 W program / 4.800 W peak at 8 Ω
Sound pressure	130 dB SPL AES / 133 dB SPL program / 136 dB SPL peak
Components	1 x 18" Woofer with 4" voice coil
Connectors	2 x Neutrik NL4 Speakon IN/OUT (loop through), configuration: 2+/2-
Dimensions	580 (h) x 580 (w) x 780 mm (d)
Amplifier	4.6 kW, three channels
Power output CH1	2.600 W/ 8 Ω, 2.200 W/ 4 Ω
Power output CH2 & CH3	750 W/ 8 Ω, 1.000 W/ 4 Ω, 750 W/ 2 Ω

