



Combi-12-Flexi

2 x Flexi-8

2 x Ventus-12

Amplifier recommendation:

2 x Powersoft T304, 4 x 750 W/8 Ω, 4 x 750 W/4 Ω

2 x Powersoft T604, 4 x 1.250 W/8 Ω, 4 x 1.500 W/4 Ω

Combi-12sp-Flexi

2 x Flexi-8

1 x Ventus-12

1 x Ventus-12sp

Flexi-8

Frequency range	65 Hz - 23 kHz (- 10 dB) 90 Hz - 22 kHz (+/- 3 dB)
Coverage range	asymmetric 100° to 50° x 55°
Power handling	200 W AES / 400 W program / 800 W peak at 8 Ω
Sound pressure	116 dB SPL AES / 119 dB SPL program / 122 dB SPL peak
Components	LF: 1 x 8" Bass-midrange driver HF: 1 x 1" Compression driver
Connectors	2 x Neutrik NL4 Speakon IN/OUT (loop through), configuration: 1+/-
Dimensions	474 (h) x 258 (w) x 282,2 mm (d)

Ventus-12/12sp

Lower cut-off frequency	37 Hz (- 10 dB) 46 Hz (+/- 3 dB)
Power handling	1.000 W AES / 2.000 W program / 4.000 W peak at 8 Ω
Sound pressure	126 dB SPL AES / 129 dB SPL program / 132 dB SPL peak
Components	1 x 12" woofer with 4" voice coil
Connectors	2 x Neutrik NL4 Speakon IN/OUT (loop through), configuration: 2+/-
Dimensions	368 (h) x 480 (w) x 500 mm (d)
Amplifier	4.6 kW, three channels
Power output CH1	2.600 W/ 8 Ω, 2.200 W/ 4 Ω
Power output CH2 & CH3	750 W/ 8 Ω, 1.000 W/ 4 Ω, 750 W/ 2 Ω

